

## 10/100 Mbps Ethernet to Multi Mode SC/ST Fiber Media Converter - 2 km

ET90110SC2 / ET90110ST2

DE: Bedienungsanleitung - de.startech.com

FR: Guide de l'utilisateur - fr.startech.com

ES: Guía del usuario - es.startech.com

IT: Guida per l'uso - it.startech.com

NL: Gebruiksaanwijzing - nl.startech.com

PT: Guia do usuário - pt.startech.com

### Packaging Contents

- 1 x Fiber Media Converter
- 1 x Universal Power Adapter
- 3 x Power Adapter Plug (NA/ UK/ EU)
- 1 x Instruction Manual

### System Requirements


- 10BASE-T or 100Base-TX compatible Ethernet network equipment
- RJ45 terminated UTP Cat5 or better Ethernet cable
- 100BASE-FX compatible fiber optic network equipment
- SC or ST terminated multi mode fiber optic cable
- Available AC electrical outlet

### Installation


1. Make sure the DIP switches are set appropriately for your network configuration (see "DIP Switch Settings" section for details).
2. Connect the fiber optic network cable from a computer/switch/ media converter to the SC/ST connector on the media converter.

**NOTE:** When connecting the fiber cable, make sure to connect the Tx (transmit) terminal on one end, with the Rx (receive) terminal on the other end.

3. Connect a UTP Ethernet cable, from a computer/switch to the RJ45 jack on the media converter.
4. Connect the power adapter to the media converter.
5. The following example illustrates the connection scheme when connecting from a 10BASE-T or 100BASE-TX Ethernet port of a hub/switch to a 100BASE-FX port of another hub/switch, through the fiber media converter:




#### ET90110SC2



\*actual product may vary from photos

#### ET90110ST2



#### Rear View (ET90110SC2/ET90110ST2)



6. The following example illustrates the connection scheme when connecting from a 100BASE-TX Ethernet port on a hub/switch to a 100BASE-TX Ethernet Network Interface Card (NIC) in a computer through the fiber media converter:



# DIP Switch Settings

## LFP:

Link Fault Pass-through will pass a link failure to the Ethernet side, if a link failure is encountered on the fiber side and vice versa.

Otherwise, the Ethernet side will continue to show no link failures, even if the fiber side has no link. (OFF = Not active, On = Active)

## Full/ Half:

Ethernet Duplex mode will be configured for Full or Half.

## 10/ 100:

Set the Ethernet side link speed to 10 or 100 Mbps.

## Auto/Manual:

Auto negotiate Link Speed and Duplex mode or manually set via DIP switches.

# LED Status

LED	Name	Status	Description
PWR	Power	ON	Unit is powered
		OFF	Unit is not powered
FEF	Far End Fault	ON	Link Fault on far end device
		OFF	No Link Faults
LNK (FX)	Fiber Link	ON	Fiber link is detected
		OFF	Fiber link is not detected
		Blink	Data transmission
100	Ethernet Link Speed	ON	100 Mbps
		OFF	10 Mbps
Full	Ethernet Duplex Mode	ON	Full Duplex Mode
		OFF	Half Duplex Mode
LNK (TX)	Ethernet Link	ON	Ethernet Link detected
		OFF	Ethernet Link not detected
		Blink	Data Transmission

# Specifications

	ET90110SC2	ET90110ST2
<b>Supported Standards</b>	IEEE 802.3, IEEE 802.3u	
<b>Connectors</b>	1 x RJ45 Ethernet female 2 x SC Fiber female 1 x DC Power	1 x RJ45 Ethernet female 2 x ST Fiber female 1 x DC Power
<b>Compatible Fiber Type</b>	Multi Mode	
<b>Optical Wavelength</b>	1310 nm	
<b>Maximum Distance</b>	2 km (1.2mi)	
<b>Duplex Modes</b>	Full/Half	
<b>Auto MDIX</b>	Yes (Ethernet)	
<b>Power Adapter</b>	12V DC, 1000mA, center positive, type M plug	
<b>Enclosure Material</b>	Metal	
<b>Operating Temperature</b>	0°C ~ 60°C (32°F ~ 140°F)	
<b>Storage Temperature</b>	-10°C ~ 70°C (14°F ~ 158°F)	
<b>Humidity</b>	10% ~ 90% RH	
<b>Dimensions (LxWxH)</b>	160.0mm x 95.0mm x 20.0mm	
<b>Weight</b>	600g	

## FCC Compliance Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

## Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. Regardless of any direct acknowledgement elsewhere in the body of this document, StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

## Technical Support

StarTech.com's lifetime technical support is an integral part of our commitment to provide industry-leading solutions. If you ever need help with your product, visit [www.startech.com/support](http://www.startech.com/support) and access our comprehensive selection of online tools, documentation, and downloads.

For the latest drivers/software, please visit [www.startech.com/downloads](http://www.startech.com/downloads)

## Warranty Information

This product is backed by a two year warranty.

In addition, StarTech.com warrants its products against defects in materials and workmanship for the periods noted, following the initial date of purchase. During this period, the products may be returned for repair, or replacement with equivalent products at our discretion. The warranty covers parts and labor costs only. StarTech.com does not warrant its products from defects or damages arising from misuse, abuse, alteration, or normal wear and tear.

## Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.