

KRAMER ELECTRONICS LTD.

USER MANUAL

MODEL:

VM-1021N

1:20 Video Distributor

P/N: 2900-300429 Rev 1



VM-1021N Quick Start Guide

This guide helps you install and use your product for the first time. For more detailed information, go to http://bit.ly/k-prod-downloads to download the latest manual or scan the QR code on the left.

Step 1: Check what's in the box

WI-1021N 1:20 Video Distributor 4 Rubber feet 1 Power cord

1 Quick Start sheet



Step 2: Install the VM-1021N

Mount the VM-1021N in a rack (using the included rack "ears") or attach the rubber feet and place on a table.

Step 3: Connect the inputs and outputs

Always switch off the power on each device before connecting it to your VM-1021N.



Always use Kramer high-performance cables for connecting AV equipment to the VM-1021N.

Step 4: Connect the power

Connect the power cord to the VM-1021N and plug it into the mains electricity.



Step 5: Operate the VM-1021N

Adjust the EQ and the LEVEL as needed with a small screwdriver.



Contents

1	Introduction	1
2	Getting Started	2
2.1	Achieving the Best Performance	2
2.2	Safety Instructions	3
2.3	Recycling Kramer Products	3
3	Overview	4
4	Installing in a Rack	7
5	Connecting the VM-1021N	8
6	VM-1021N Technical Specifications	10

Figures

Figure 1: VM-1021N 1:20 Video Distributor Front Panel	5
Figure 2: VM-1021N 1:20 Video Distributor Rear Panel	6
Figure 3: Connecting the VM-1021N	8

1 Introduction

Welcome to Kramer Electronics! Since 1981, Kramer Electronics has been providing a world of unique, creative, and affordable solutions to the vast range of problems that confront the video, audio, presentation, and broadcasting professional on a daily basis. In recent years, we have redesigned and upgraded most of our line, making the best even better!

Our 1,000-plus different models now appear in 14 groups that are clearly defined by function: GROUP 1: Distribution Amplifiers; GROUP 2: Switchers and Routers; GROUP 3: Control Systems; GROUP 4: Format/Standards Converters; GROUP 5: Range Extenders and Repeaters; GROUP 6: Specialty AV Products; GROUP 7: Scan Converters and Scalers; GROUP 8: Cables and Connectors; GROUP 9: Room Connectivity; GROUP 10: Accessories and Rack Adapters; GROUP 11: Sierra Video Products; GROUP 12: Digital Signage; GROUP 13: Audio; and GROUP 14: Collaboration.

Congratulations on purchasing your Kramer **VM-1021NN** distribution amplifier that is ideal for the following typical applications:

- Broadcast, production, or presentation systems requiring high-quality signal distribution
- Schools, retail, sports bars, other point-of-sale and CCTV applications
- Computer RGB or component video distribution

2 Getting Started

We recommend that you:

- Unpack the equipment carefully and save the original box and packaging
 materials for possible future shipment
- Review the contents of this user manual



Go to <u>http://www.kramerelectronics.com/support/product_downloads.asp</u> to check for up-to-date user manuals, application programs, and to check if firmware upgrades are available (where appropriate).

2.1 Achieving the Best Performance

To achieve the best performance:

- Use only good quality connection cables (we recommend Kramer highperformance, high-resolution cables) to avoid interference, deterioration in signal quality due to poor matching, and elevated noise levels (often associated with low quality cables)
- Do not secure the cables in tight bundles or roll the slack into tight coils
- Avoid interference from neighboring electrical appliances that may adversely influence signal quality
- Position your Kramer VM-1021N away from moisture, excessive sunlight and dust



This equipment is to be used only inside a building. It may only be connected to other equipment that is installed inside a building.

2.2 Safety Instructions

Caution:	There are no operator serviceable parts inside the unit
Warning:	Use only the power cord that is supplied with the unit
Warning:	Do not open the unit. High voltages can cause electrical shock! Servicing by qualified personnel only
Warning:	Disconnect the power and unplug the unit from the wall before installing
	Caution: Warning: Warning: Warning:

2.3 Recycling Kramer Products

The Waste Electrical and Electronic Equipment (WEEE) Directive 2002/96/EC aims to reduce the amount of WEEE sent for disposal to landfill or incineration by requiring it to be collected and recycled. To comply with the WEEE Directive, Kramer Electronics has made arrangements with the European Advanced Recycling Network (EARN) and will cover any costs of treatment, recycling and recovery of waste Kramer Electronics branded equipment on arrival at the EARN facility. For details of Kramer's recycling arrangements in your particular country go to our recycling pages at <u>http://www.kramerelectronics.com/support/recycling/</u>.

3 Overview

The **VM-1021N** is a high-performance distribution amplifier for composite or SDI video signals. It provides controls to compensate for signal losses inherent in long cable runs.

The **VM-1021N** is a full broadcast, state-of-the-art, 1:20 video distribution amplifier designed for studio and other demanding applications. The unit splits a single input source into twenty identical outputs with no discernible signal degradation. The outputs are divided into 4 sets of five each, where each set may be individually trimmed (level and EQ) for maximal flexibility. The machine may be used to distribute analog or SD-SDI video signals, composite or single component.

The unit features:

- High bandwidth of 350MHz (-3dB)
- Grouped level (gain) and EQ (peaking) controls
- Looping inputs
- Selectable input signal termination
- DC coupling
- Standard 19" rack mount size of 1U

Figure 1 and Figure 2 define the unit.



Figure 1: VM-1021N 1:20 Video Distributor Front Panel

#	Feature	Function
1	POWER LED	Illuminates when the device is turned on
2	SET 4 ADJUST EQ Trimmer	Controls cable equalization of SET 4 video outputs 16-20
3	SET 4 ADJUST LEVEL Trimmer	Controls level of SET 4 video outputs 16-20
4	SET 3 ADJUST EQ Trimmer	Controls cable equalization of SET 3 video outputs 11-15
5	SET 3 ADJUST LEVEL Trimmer	Controls level of SET 3 video outputs 11-15
6	SET 2 ADJUST EQ Trimmer	Controls cable equalization of the SET 2 video outputs 6-10
7	SET 2 ADJUST LEVEL Trimmer	Controls level of SET 2 video outputs 6-10
8	SET 1 ADJUST EQ Trimmer	Controls cable equalization of the SET 1 video outputs 1-5
9	SET 1 ADJUST LEVEL Trimmer	Controls level of the SET 1 video outputs 1-5

VM-1021N - Overview



Figure 2: VM-1021N 1:20 Video Distributor Rear Panel

#	Feature	Function
10	INPUT BNC Connector	Connects to a composite/component/ analog sync video source
11	LOOP BNC Connector	Selects "75Ω" or "HI-z" impedance when pressed (for looping select "Hi-z")
12	IN=75Ω Button	Provides video looping capability to increase number of outputs
13	OUT SET 1 BNC Connectors (1-5)	SET 1 of 5 amplified buffered and clamped video outputs 1-5
14	OUT SET 2 BNC Connectors (6-10)	SET 2 of 5 amplified buffered and clamped video outputs 6-10
15	OUT SET 3 BNC Connectors (11-15)	SET 3 of 5 amplified buffered and clamped video outputs 11-15
16	OUT SET 4 BNC Connectors (16-20)	SET 4 of 5 amplified buffered and clamped video outputs 16-20
17	Power Connector	AC connector, fuse and power switch enabling power supply to the unit

4 Installing in a Rack

This section provides instructions for rack mounting the unit.

Before installing in a rack, be sure that the environment is within the recommended range:

OPERATING TEMPERATURE:	0° to +40°C (32° to 104°F)
STORAGE TEMPERATURE:	-40° to +70°C (-40° to 158°F)
HUMIDITY:	10% to 90%, RHL non-condensing

To rack-mount a machine:

1. Attach both ear brackets to the machine. To do so, remove the screws from each side of the machine (3 on each side), and replace those screws through the ear brackets.



 Place the ears of the machine against the rack rails, and insert the proper screws (not provided) through each of the four holes in the rack ears. Note:

• In some models, the front panel

may feature built-in rack ears • Detachable rack ears can be removed for desktop use

 Always mount the machine in the rack before you attach any cables or connect the machine to the power

 If you are using a Kramer rack adapter kit (for a machine that is not 19"), see the Rack Adapters user manual for installation instructions available from our Web site



CAUTION!

When installing on a 19" rack, avoid hazards by taking care that:

1. It is located within the recommended environmental conditions, as the operating ambient temperature of a closed or multi unit rack assembly may exceed the room ambient temperature.

2. Once rack mounted, enough air will still flow around the machine.

3. The machine is placed straight in the correct horizontal position.

4. You do not overload the circuit(s). When connecting the machine to the supply circuit, overloading the circuits might have a detrimental effect on overcurrent protection and supply wiring. Refer to the appropriate nameplate ratings for information. For example, for fuse replacement, see the value printed on the product label.

5. The machine is earthed (grounded) in a reliable way and is connected only to an electricity socket with grounding. Pay particular attention to situations where electricity is supplied indirectly (when the power cord is not plugged directly into the socket in the wall), for example, when using an extension cable or a power strip, and that you use only the power cord that is supplied with the machine.

5 Connecting the VM-1021N



Always switch off the power to each device before connecting it to your **VM-1021N**. After connecting your **VM-1021N**, connect its power and then switch on the power to each device.

To connect the VM-1021N as illustrated in the example in Figure 3:

- Connect a video source to the INPUT BNC connector (for example, a composite video player).
- Connect the OUT SET BNC connectors to up to 20 video acceptors, 4 sets of 5 devices (for example, composite video displays with speakers).
- Adjust the equalization (EQ) and level (LEVEL) for each of the 4 sets of 5 devices as needed.



Figure 3: Connecting the VM-1021N

Note:

- Terminate unused inputs to 75Ω, and terminate active inputs at the connecting source
- The output signal format must match the input signal format (for example, if the input is composite, the output is composite)
- All signal cables to each device should be of equal length (for example, the R,G,B cables between a camera and the amplifier should be of equal length)

6 VM-1021N Technical Specifications

INPUT:	1 composite video or a single component, looping, $1Vpp/75\Omega$ on BNC connectors with termination switch
OUTPUTS:	20 composite/component video, 1Vpp/75Ω on BNC connectors
VIDEO BANDWIDTH(-3dB):	350MHz
DIFF. GAIN:	0.1%
DIFF. PHASE:	0.07Deg
K-FACTOR:	<0.05%
VIDEO S/N RATIO:	74dB
CONTROL:	Level: -1.1dB to + 2.7dB; EQ.: 0 to 2.9dB @4.4MHz
NON-LINEARITY:	0.1%
COUPLING:	DC
POWER SOURCE:	100-240V AC, 50/60Hz, 6.7VA
OPERATING TEMPERATURE:	0° to +40°C (32° to 104°F)
STORAGE TEMPERATURE:	-40° to +70°C (-40° to 158°F)
HUMIDITY:	10% to 90%, RHL non-condensing
DIMENSIONS:	19" x 7" x 1U W, D, H, rack mountable
WEIGHT:	2.6kg (5.7lbs) approx.
INCLUDED ACCESSORIES:	Power cord
Specifications are subject to change without notice at http://www.kramerelectronics.com	

LIMITED WARRANTY

The warranty obligations of Kramer Electronics for this product are limited to the terms set forth below:

What is Covered

This limited warranty covers defects in materials and workmanship in this product.

What is Not Covered

This limited warranty does not cover any damage, deterioration or malfunction resulting from any alteration, modification, improper or unreasonable use or maintenance, misuse, abuse, accident, neglect, exposure to excess moisture, fire, improper packing and shipping (such claims must be presented to the carrier), lightning, power surges, or other acts of nature. This limited warranty does not cover any damage, deterioration or malfunction resulting from the installation or removal of this product from any installation, any unauthorized tampering with this product, any repairs attempted by anyone unauthorized by Kramer Electronics to make such repairs, or any other cause which does not relate directly to a defect in materials and/or workmanship of this product. This limited warranty does not cover cartons, equipment enclosures, cables or accessories used in conjunction with this product.

Without limiting any other exclusion herein, Kramer Electronics does not warrant that the product covered hereby, including, without limitation, the technology and/or integrated circuit(s) included in the product, will not become obsolete or that such items are or will remain compatible with any other product or technology with which the product may be used. How Long Does this Coverage Last

Seven years as of this printing; please check our Web site for the most current and accurate warranty information. Who is Covered

Only the original purchaser of this product is covered under this limited warranty. This limited warranty is not transferable to subsequent purchasers or owners of this product.

What Kramer Electronics will do

Kramer Electronics will, at its sole option, provide one of the following three remedies to whatever extent it shall deem necessary to satisfy a proper claim under this limited warranty:

- 1. Elect to repair or facilitate the repair of any defective parts within a reasonable period of time, free of any charge for the necessary parts and labor to complete the repair and restore this product to its proper operating condition. Kramer Electronics will also pay the shipping costs necessary to return this product once the repair is complete.
- 2. Replace this product with a direct replacement or with a similar product deemed by Kramer Electronics to perform substantially the same function as the original product.
- 3 Issue a refund of the original purchase price less depreciation to be determined based on the age of the product at the time remedy is sought under this limited warranty.

What Kramer Electronics will not do Under This Limited Warranty If this product is returned to Kramer Electronics or the authorized dealer from which it was purchased or any other party authorized to repair Kramer Electronics products, this product must be insured during shipment, with the insurance and shipping charges prepaid by you. If this product is returned uninsured, you assume all risks of loss or damage during shipment. Kramer Electronics will not be responsible for any costs related to the removal or re-installation of this product from or into any installation. Kramer Electronics will not be responsible for any costs related to any setting up this product, any adjustment of user controls or any programming required for a specific installation of this product.

How to Obtain a Remedy under this Limited Warranty

To obtain a remedy under this limited warranty, you must contact either the authorized Kramer Electronics reseller from whom you purchased this product or the Kramer Electronics office nearest you. For a list of authorized Kramer Electronics resellers and/or Kramer Electronics authorized service providers, please visit our web site at www.kramerelectronics.com or contact the Kramer Electronics office nearest you.

In order to pursue any remedy under this limited warranty, you must possess an original, dated receipt as proof of purchase from an authorized Kramer Electronics reseller. If this product is returned under this limited warranty, a return authorization number, obtained from Kramer Electronics, will be required. You may also be directed to an authorized reseller or a person authorized by Kramer Electronics to repair the product.

If it is decided that this product should be returned directly to Kramer Electronics, this product should be properly packed, preferably in the original carton, for shipping. Cartons not bearing a return authorization number will be refused.

Limitation on Liability

THE MAXIMUM LIABILITY OF KRAMER ELECTRONICS UNDER THIS LIMITED WARRANTY SHALL NOT EXCEED THE ACTUAL PURCHASE PRICE PAID FOR THE PRODUCT. TO THE MAXIMUM EXTENT PERMITTED BY LAW, KRAMER ELECTRONICS IS NOT RESPONSIBLE FOR DIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES RESULTING FROM ANY BREACH OF WARRANTY OR CONDITION, OR UNDER ANY OTHER LEGAL THEORY. Some countries, districts or states do not allow the exclusion or limitation of relief, special, incidental, consequential or indirect damages, or the limitation of liability to specified amounts, so the above limitations or exclusions may not apply to you.

Exclusive Remedy

TO THE MAXIMUM EXTENT PERMITTED BY LAW, THIS LIMITED WARRANTY AND THE REMEDIES SET FORTH ABOVE ARE EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES, REMEDIES AND CONDITIONS, WHETHER ORAL OR WRITTEN, EXPRESS OR IMPLIED. TO THE MAXIMUM EXTENT PERMITTED BY LAW, KRAMER ELECTRONICS SPECIFICALLY DISCLAIMS ANY AND ALL IMPLIED WARRANTIES, INCLUDING, WITHOUT LIMITATION, WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. IF KRAMER ELECTRONICS CANNOT LAWFULLY DISCLAIM OR EXCLUDE IMPLIED WARRANTIES UNDER APPLICABLE LAW, THEN ALL IMPLIED WARRANTIES COVERING THIS PRODUCT, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, SHALL APPLY TO THIS PRODUCT AS PROVIDED UNDER APPICABLE LAW.

APPLI TO THIS PRODUCT TO WHICH THIS LIMITED WARRANTY APPLIES IS A "CONSUMER PRODUCT" UNDER THE MAGNUSON-MOSS WARRANTY ACT (15 U.S.C.A. §2301, ET SEQ.) OR OTHER APPICABLE LAW, THE FOREGOING DISCLAIMER OF IMPLIED WARRANTIES SHALL NOT APPLY TO YOU, AND ALL IMPLIED WARRANTIES ON THIS PRODUCT, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR THE PARTICULAR PURPOSE, SHALL APPLY AS PROVIDED UNDER APPLICABLE LAW.

Other Conditions

This limited warranty gives you specific legal rights, and you may have other rights which vary from country to country or state to state.

This limited warranty is void if (i) the label bearing the serial number of this product has been removed or defaced, (ii) the product is not distributed by Kramer Electronics or (iii) this product is not purchased from an authorized Kramer Electronics reseller. If you are unsure whether a reseller is an authorized Kramer Electronics reseller, please visit our Web site at

www.kramerelectronics.com or contact a Kramer Electronics office from the list at the end of this document

Your rights under this limited warranty are not diminished if you do not complete and return the product registration form or complete and submit the online product registration form. Kramer Electronics thanks you for purchasing a Kramer Electronics product. We hope it will give you years of satisfaction.



For the latest information on our products and a list of Kramer distributors, visit our Web site where updates to this user manual may be found.

We welcome your questions, comments, and feedback. Web site: <u>www.kramerelectronics.com</u>

E-mail: info@kramerel.com

