

ANY SPOT[®]

WIRELESS MICROPHONE SYSTEM

EDX

The EDX Series is a dual channel wireless microphone system. The EDX features 2 internal antennas (1 for each receiver), 16 selectable UHF frequencies on each receiver, and IR Sync transmitters to receiver. The EDX has 2 discreet male XLR outputs and 1 combined 1/4" output on the back of the unit. The output is controlled by a volume control for each receiver, located on the front of the unit.

**IR
SYNC**

The EDXR can be used and will sync with either the HH38 handheld or the MBP38 body pack transmitters. Systems with the MBP38 body pack are available with either a lavalier, or headset. Both transmitters feature an on/off switch and are powered by two "AA" batteries. The MBP38 body pack transmitter also features a Mic/0/-10 selector switch for various input level sources.

EDX System

- 200' Range
- 16 Selectable Frequencies
- Internal Antennas

EDXR Receiver

- Dual Channel Receiver
- AF & RF Level Indicators
- IR Sync Transmitter to Receiver
- 1 Mixed 1/4" Output, Two Balanced Male XLR Outputs
- 2 Internal Antennas (Non-Diversity)
- Rugged Plastic Casing



EDX OPTIONS - OTHER OPTIONS INCLUDE THE HH38 HANDHELD OR MBP38 BODY PACK

**DUAL
HANDHELD
EDXR/
HH38**



**HANDHELD/
HEADSET
EDXR/
HHBP5**



**HANDHELD/
LAVALIER
EDXR/
HHBPV**



**DUAL
LAVALIER
EDXR/
38VV**



**HEADSET/
LAVALIER
EDXR/
385V**



**DUAL
HEADSET
EDXR/
3855**



**UPGRADE YOUR SYSTEM
WITH A GREAT
HEADSET MIC**

EDXR/38

ESM8

ESM3

HSM8

HSM3



MAKERS OF THE ORIGINAL
HOT SPOT PERSONAL MONITOR



ANY SPOT[®]

WIRELESS MICROPHONE SYSTEM

EDX

Specifications:

EDX System

Available Channels: 16

Transmitter Output Level: 10 mW

Band: UHF

Operating Range: Under Typical Conditions 200' (61 m), actual range depends on RF signal absorption, reflection, and interference.

Audio Frequency Response: (+/-3 dB) 60 Hz - 16 kHz

Total Harmonic Distortion: (+/-30 kHz deviation 1 kHz tone): <1%

Dynamic Range: >90 dB A-weighted

Operating Temperature Range: 14°F to 122°F (-10°C to 50°C), battery characteristics may limit this range.

Included Accessories: Power Supply, 1/4" to 1/4" Audio Cable x1, Quick Start Guide

Receiver (EDXR)

Audio Output Level: XLR Connector (into 600 Ohms load) -12dBV

1/4" Connector (into 3k Ohms load) -18dBV

Output Impedance: XLR Connector 200 Ohms

1/4" Connector 1k Ohms

XLR Output: Impedance balanced

Pin 1: Ground (cable shield)

Pin 2: Audio +

Pin 3: No Audio -

Sensitivity: -92dBm

Image Rejection: >92dB

Dimensions: 1.7" x 8.3" x 5" (42 x 210 x 127 mm)(HxWxD)

Weight: 13.6 oz (390 g)

Power Requirements: 12-18 V dc at 300mA, supplied by external power supply

Dynamic Cardioid Handheld Transmitter (HH38)

Max Audio Input Level: 0dBV

Gain Adjust: Trim pot

RF Output: 10 mW

Frequency Response: 70Hz - 10kHz

Dimensions: 10.8" x 1.9" (275 x 47 mm) (LxDia.)

Weight: 6.9 oz (195 g) (without batteries)

Power Requirements: 2 "AA" Batteries, alkaline or rechargeable

Battery Life: About 8 hours (alkaline)

Body Pack Transmitter (MBP38)

Max Audio Input Level: 0dBV to +20dBV

Gain Adjust: Mic / 0dB / -10dB

RF Output: 10 mW

Input Impedance: 5k Ohms

Dimensions: 3.3" x 2.6" x 1" (85 x 65 x 23 mm) (HxWxD)

Weight: 2.8 oz (80 g) (without batteries)

Power Requirements: 2 "AA" Batteries, alkaline or rechargeable

Battery Life: About 8 hours (alkaline)



EDXR Receiver



BACK VIEW



MBP38

HH38

FREQUENCY CODES

CODE D 584-607 MHz

CODE L 655-679 MHz

CODE N 518-535 MHz



MAKERS OF THE ORIGINAL
HOT SPOT PERSONAL MONITOR

601 E. Pawnee Wichita, KS 67211 316. 263.2852 FAX 316.263.0642 www.galaxyaudio.com
Distributed in Canada by Audio Distributors International (ADI) 1275 Newton, unit 6 Boucherville, QC J4B 5H2 Canada
450.449.8177 FAX 450.449.8180
Distributed outside the United States by TradeLink America, LLC. 230 Kings Mall Ct., Suite 182 Kingston, NY 12401
MikeH@TradeLinkAmerica.com TEL 1.845.246.6200 FAX 1.845.746.9070

Specifications subject to change without notice.

V20171010