



# KRAMER

## 908

Stereo Amplifier & Switcher (40 Watts per Channel)

| Speakers | Ethernet - RJ-45



The 908 is a highperformance audio amplifier for linelevel stereo audio signals. It accepts either a balanced or an unbalanced stereo audio signal and delivers a speaker output of 40 watts RMS per channel into 8 loads

## FEATURES

**High Efficiency** - Class D operation

**Controls** - Control knob to adjust volume, bass, middle, treble and balance. Mute and loudness buttons, plus a 10V control port for adjusting the audio gain

**USB Port** - For firmware update

**Flexible Control Options** - Front panel, RS232 (KRouter™ Windows®based software is included), Ethernet, IR remote (included) and 10K volume level



# KRAMER

## TECHNICAL SPECIFICATIONS

---

INPUTS:	1 unbalanced stereo audio on RCA connectors; 1 balanced stereo audio on a 5pin terminal block connector; 1 USB connector
OUTPUT:	1 speaker stereo audio on a 4pin terminal block connector
INPUT SENSITIVITY:	Unbalanced: 360mVpp; balanced: 220mVpp
MAX. VOLTAGE GAIN:	Unbalanced: 35dB; balanced: 40.5dB
OUTPUT POWER:	40W per channel into 8
BANDWIDTH (-3dB):	22kHz
CROSSTALK:	<57dB @20kHz
CONTROLS:	Level: <30dB to 35.5dB; balance: 30dB to 0dB; loudness: 14dB to 0dB @1kHz; bass: 15dB to 12dB @100Hz; mid: 15dB to 11dB @1kHz; treble: 14dB to 13dB @10kHz; input selector buttons, mute button, loudness, bass, mid, treble, balance, volume buttons, IR, RS232, Ethernet, 10V volume control, 1 USB port for upgrading firmware
COUPLING:	Input: AC, output: DC
AUDIO THD + NOISE:	0.15%
AUDIO 2nd HARMONIC:	0.06%
SIGNAL/NOISE RATIO:	63dB, 80dB @10% distortion
AMPLIFIER TYPE:	Class D
POWER CONSUMPTION:	24V DC, 2A
INCLUDED ACCESSORIES:	Power supply, Windows®based Kramer control software, IR remote control transmitter
OPTIONS:	RKT2B 19" rack adapter
PRODUCT DIMENSION:	18.75cm x 11.50cm x 2.54cm (7.38" x 4.53" x 1.00" ) W, D, H
PRODUCT WEIGHT:	0.5kg (1.1lbs) approx
SHIPPING DIMENSION:	34.50cm x 16.50cm x 5.20cm (13.58" x 6.50" x 2.05" ) W, D, H
SHIPPING WEIGHT:	1.4kg (3.1lbs) approx

