



FR-355K

The microphones in the **MXL FR-355K** kit were designed with high quality FET pre-amps to ensure outstanding audio quality even under the most demanding conditions. The **FR-355K** kit contains 2 different microphones. The **FR-351** cardioid mic has a 8mm capsule, while the **FR-350** omni mic has a 6mm capsule. These lavalier microphones require 48v phantom power to operate. They are both supplied with foam windscreens and clips.

SPECIFICATIONS

FR-350

Type	Electret Condenser Microphone
Polar Pattern	Omn-directional
Frequency Response	40-15000Hz
Max SPL	120 dB
Sensitivity	10mV/Pa, -40dB±2dB, 2500Ω, 0dB=1v/Pa
Output Impedance	200 ohms
Power Requirement	48V Phantom Power
Signal-to-Noise Ratio	72 dB
Accessories	Windscreen

FR-351

Type	Electret Condenser Microphone
Polar Pattern	Cardioid
Frequency Response	40-15000Hz
Maximum Sound Input Level	120 dB
Sensitivity	10mV/Pa, -40dB±2dB, 2500Ω, 0dB=1v/Pa
Output Impedance	200 ohms
Power Requirement	48V Phantom Power
Signal-to-Noise Ratio	72 dB
Accessories	Windscreen

