

MX410



ROLLS

4 CHANNEL FIELD/ENG MIXER

FEATURES

- Four balanced XLR Inputs
- Two transformer-balanced XLR Outputs
- Switchable Output Level (Line level, or Mic level)
- 1/8" TRS Stereo Auxiliary Input
- Switchable Phantom Power for each input
- Switchable 100 Hz Low Cut filters for each input
- Dual 9V easy access Battery compartment
- Level controls for each channel
- 1/8" (3.5mm) Headphone Output - Level control
- 18 hour battery life
- phones attached, constant use).
- Rolls PS27 external power supply included

ROLLS

4 CHANNEL

ENG/

FIELD MIXER

BALANCED XLR INPUTS
BALANCED XLR OUTPUTS
HEADPHONE OUT
3.5mm CAMERA OUTPUT

ROLLS

5968 SOUTH 350 WEST S.L.C.,UT 84107

PHONE: 801-263-9053

FAX: 801-236-9068



The MX410 is a professional 4 channel ENG/Field Mixer, designed with ease of use in mind. The MX410 is constructed from a powder coated steel chassis. Locking XLR's and a recessed power switch make the MX410 a great choice for professional sound applications. The MX410 is designed to operate with two 9 volt batteries or can be powered with the included Rolls PS27 adapter. Every high end field mixer should be supplied with a bag and sholder strap the MX410 has both included. The bag is designed specifically for the MX410 for a professional fit.

SPECIFICATIONS

Input Impedance:	Mic:	600 Ohms XLR balanced
Output Attenuator:		-30 dB
Self Noise:		-65 dB maximum -90 dB typical
Max Gain:		+55 db
S/N Ratio:		115 dB
THD:		.05%
Frequency Response:		20 Hz - 20 kHz +0, -3 dB
Low Cut:		100 Hz
Max Input:		-20 dBV
Current Draw:		30 mA with no Phantom Power or Signal.
Phantom Power:		+18 VDC
Typical Battery Life:		18 Hrs. (2 mics, phan on, with headphone)
Connectors:		4 ea. Female XLR, 2 ea. Male XLR, 3 ea. 1/8" (3.5mm), 1 Center Negative power jack.
Power Adapter:		12VDC / 200 mA
Size:		9" W x 6.75" D x 1.5" H
Weight:		2.45 lbs

MSRP: \$399 USD

Power Supply Included



MADE IN USA



6 75889 04100 2