

# SONIFEX

Redbox RB-MA2
August 2008



www.sonifex.co.uk t: +44 (0)1933 650 700 f: +44 (0)1933 650 726 sales@sonifex.co.uk



### **Redbox - Microphone Amplifiers & Limiters**

#### **RB-MA2 Dual Microphone Amplifier**

The RB-MA2 consists of two independent low-noise microphone pre-amplifiers for converting mic level signals to line level, or for driving long lines from microphones to processing equipment.

All connections and controls are on the rear panel. The microphone inputs are XLR-3 type and are electronically balanced. The input gain for each input can be adjusted individually by a recessed pre-set potentiometer which allows for the use of both dynamic and powered microphones.

The XLR-3 line outputs are electronically balanced and can be wired unbalanced by grounding the non-phase signal,

All the Redboxes are screw mountable as standard and are either rack-mounted or have the option to be rack-mounted.

allowing you to feed both balanced and unbalanced equipment.

For each channel there are independent switches to control a high pass filter (low frequency roll-off at 125Hz) and to provide phantom power at +48V to the connected microphones.









Fuse Kating:	Anti-
	(230)
	Anti-

Mains Input:

RB-MA2

-surge fuse 100mA 20 x 5mm VAC) surge fuse 250mA 20 x 5mm (115VAC) **Equipment Type** 

Dual microphone amplifier

Filtered IEC, switchable 110-120V, or 220-240V, fused, 6W max

28cm (W) x 10.8cm (D) x 4.2cm (H) (1U) Dimensions 11" (W) x 4.3" (D) x 1.7" (H) (1U) Dimensions 36cm (W) x 20.5cm (D) x 6cm (H) (Boxed): 14.2" (W) x 8" (D) x 2.4" (H) Weight RB-MA2: Nett: 1.00kgGross: 1.45kg Nett: 2.2lbs Gross: 3.2lbs

## SONIFEX

www.sonifex.co.uk

t:+44 (0)1933 650 700 f:+44 (0)1933 650 726 sales@sonifex.co.uk

61 Station Road Irthlingborough Northants NN9 5QE United Kingdom

