

2.9kW Single-Phase ATS / Metered PDU, 120V Outlets (24 5-15/20R, 1 L5-30R), 2 L5-30P, 2 10ft Cords, 2U Rack-Mount

MODEL NUMBER: PDUMH30AT











Description

Tripp Lite Metered ATS / Auto Transfer Switch provides a redundant power option for single-corded network devices. Dual input cords support separate connection to PRIMARY and SECONDARY power sources. The ATS will normally maintain continuous output to all outlets as derived from the primary input cable. If the primary power source becomes unstable or fails altogether, the ATS will switch over to the secondary power source until the primary input is restored and stable. Highly reliable solid-state switching between primary and secondary power sources occurs within milliseconds. ATS functionality is supported by any two compatible AC power sources, regardless of phase angle, to support a variety of advanced redundant power networking applications. Enables fault tolerant hot-swappable UPS protection when used with a single UPS and fully redundant UPS protection when each cord is connected to a separate UPS system. In a two-UPS environment, the primary input

Highlights

- Single phase 30A 120V Auto Transfer Switch / ATS PDU; Highly reliable Solid State Switching
- Enables redundant A/B power option for single-corded network devices
- Separate primary & secondary inputs connect to any two compatible power sources
- 2U horizontal rackmount; 2
 L5-30P inputs; 24 5-15/20R & 1
 L5-30R outlets
- Digital meter reports voltage, kW load level and output amperage in 4 load segments

Applications

 Auto-Transfer Switch / Metered PDU is ideal for providing redundant A/B power to single-corded network equipment

Package Includes

- ATS / Metered PDU
- Rackmount installation brackets
- Installable plug-retention shelves
 & cable ties

cable must be supported by a full time sine wave UPS with zero transfer time. Tripp Lite SmartOnline series is highly recommended for use as the primary UPS in a two-UPS application. ATS configurations utilizing separate mains circuits, backup generators and even separate utility power grid feeds are fully supported. On-board ATS processor constantly evaluates power quality on both input sources to prevent transfer to the secondary source when unavailable or of lower quality than the primary source. Front input LED's display primary or secondary power availability.

Features

- 120V 30A Automatic Transfer Switch (ATS) / Metered PDU (Agency de-rated to 24A continuous)
- Provides a redundant A/B power option for non-redundant networking equipment with a single input power cord
- Visual meter reports output amp and kW power consumption, plus input voltage
- 2U horizontal rackmount form factor; 11.9 in. / 30.2 cm depth
- 25 outlets (24 5-15/20R, 1 L5-30R)
- Set of two 10 ft. / 3m NEMA L5-30P input line cords enable separate PRIMARY and SECONDARY input connections
- ATS circuits normally maintain output sourced from the primary input cable; As primary input power fails or becomes unstable, the ATS will switch to maintain output sourced from the secondary input cable until power on the primary input is restored and stable
- Highly reliable solid-state switching enables fast 1-5 millisecond transfer between primary and secondary inputs



- ATS configurations enable fault-tolerant, hot-swappable UPS protection when used with a single UPS and fully redundant UPS protection when each cord is connected to a separate UPS system (in a two-UPS environment, the primary input cable must be supported by an online UPS with zero transfer time similar to Tripp Lite SmartOnline series)
- Advanced ATS configurations utilizing separate mains circuits, backup generators and even separate out of phase utility power grid feeds are fully supported
- On-board ATS processor constantly evaluates power quality on both inputs to prevent transfer to the secondary source when unavailable or of lower quality than the primary source
- Front panel LEDs confirm power availability on both input lines
- TAA Compliant Version Available Order Tripp Lite PDUMH30ATAA

Specifications

OVERVIEW	
PDU Type	Auto-Transfer Switch; Metered
ОИТРИТ	
Output Capacity Details	2.88kW (120V), 3.05kW (127V), 2.4kW (100V); 30A maximum (agency de-rated to 24A continuous)
Frequency Compatibility	60 Hz
Output Receptacles	(24) 5-15/20R; (1) L5-30R
Output Nominal Voltage	100-127V nominal, single phase
Overload Protection	2 20A output breakers protect 12 5-15/20R outlets each
Outlet Type	5-15/20R, L5-30R
Individual Outlet Switching	No
INPUT	
PDU Input Voltage	100; 120; 127
Recommended Electrical Service	30A 120V
Maximum Input Amps	30
Maximum Input Amps Details	Agency de-rated to 24A continuous
PDU Plug Type	NEMA L5-30P
Input Cord Length (ft.)	10
Input Cord Length (m)	3
Input Cord Details	Two input power cords enable connection to separate Primary and Secondary input power sources
Input Phase	Single-Phase
USER INTERFACE, ALERTS & CO	NTROLS
Front Panel LCD Display	Digital display reports output amps in 4 separately metered loading segments (BANK 1: 5-20R outlets #1-12; BANK 2: 5-20R outlets #13-24; BANK 3: L5-30R outlet #25; BANK 4: Total PDU output), whole-PDU output kW load level and input voltage on primary and secondary input lines





WARRANTY	
Certifications	Tested to UL 60950-1 (USA), CSA (Canada), Class A (Emissions), NOM (Mexico), RoHS Complaint
TAA Compliant Option	TAA Compliant Version Available - Order Tripp Lite PDUMH30ATAA
CERTIFICATIONS	
TVSS Grounding	Rear grounding lug
SPECIAL FEATURES	
SNMP Compatibility	n/a
COMMUNICATIONS	T.,
Operating Elevation (m)	0-3000
Operating Elevation (ft.)	0-10,000
Relative Humidity	5-95% non-condensing
Storage Temperature Range	5 to 122F (-15 to 50C)
ENVIRONMENTAL	
PDU Form Factor	Horizontal (1U, 2U, etc)
Form Factors Supported	2U rackmount
Material of Construction	Metal
Unit Weight (kg)	6.22
Unit Weight (lbs.)	13.71
Unit Dimensions (hwd / cm)	8.66 x 44 x 30.2
Unit Dimensions (hwd / in.)	3.41 x 17.32 x 11.89
Shipping Weight (kg)	8
Shipping Weight (lbs.)	17.6
Shipping Dimensions (hwd / cm)	20.3 x 52.1 x 43.2
Shipping Dimensions (hwd / in.)	8 x 20.5 x 17
PHYSICAL	
Switches	ENTER and MODE switches toggle the digital display to show output amps (Banks 1-4), total kW output and input voltage (primary, secondary)
Front Panel LEDs	2 LEDs for power status on Primary and Secondary input connection and three additional LEDs to label the displayed numeric value as Amps, kW or Voltage



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Product Warranty Period (Worldwide)

2-year limited warranty

© 2015 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: http://www.tripplite.com/products/product-certification-agencies