


INSTALLATION INSTRUCTIONS



WITH TS118



WITH TS218

THINSTALL™ IN-WALL ENCLOSURE

DISCLAIMER

Milestone AV Technologies, and its affiliated corporations and subsidiaries (collectively, "Milestone"), intend to make this manual accurate and complete. However, Milestone makes no claim that the information contained herein covers all details, conditions or variations, nor does it provide for every possible contingency in connection with the installation or use of this product. The information contained in this document is subject to change without notice or obligation of any kind. Milestone makes no representation of warranty, expressed or implied, regarding the information contained herein. Milestone assumes no responsibility for accuracy, completeness or sufficiency of the information contained in this document.

Chief® is a trademark of Milestone AV Technologies.
All rights reserved.

IMPORTANT SAFETY INSTRUCTIONS!

 **WARNING:** A WARNING alerts you to the possibility of serious injury or death if you do not follow the instructions.

 **CAUTION:** A CAUTION alerts you to the possibility of damage or destruction of equipment if you do not follow the corresponding instructions.

 **WARNING:** Failure to read, thoroughly understand, and follow all instructions can result in serious personal injury, damage to equipment, or voiding of factory warranty! It is the installer's responsibility to make sure all components are properly assembled and installed using the instructions provided.

 **WARNING:** Failure to provide adequate structural strength for this component can result in serious personal injury or damage to equipment! It is the installer's responsibility to make sure the structure to which this component is attached can support five times the combined weight of all equipment. Reinforce the structure as required before installing the component. The wall to which the mount is being attached may have a maximum drywall thickness of 5/8" (1.6cm).

 **WARNING:** Exceeding the weight capacity can result in serious personal injury or damage to equipment! It is the installer's responsibility to make sure the structure to which this accessory is attached can support the combined weight of the box and all equipment not to exceed 75 lbs (34.0 kg). The combined weight of all components attached to the TS118SU mount cannot exceed 35 lbs (15.9 kg). The combined weight of all components attached to the TS218SU mount cannot exceed 75 lbs (34.0 kg).



WARNING: Use this mounting system only for its intended use as described in these instructions. Do not use attachments not recommended by the manufacturer.



WARNING: Never operate this mounting system if it is damaged. Return the mounting system to a service center for examination and repair.




WARNING: Do not use this product outdoors.

NOTES:

- It is the installer's responsibility to ensure that the enclosure is bonded to the ground in the switch box, in accordance with the National Electric Code, ANSI/NFPA 70 or Canadian Electrical Code, CSA C22.1. A green grounding screw is provided in the enclosure for the purpose, if required.
- The equipment shall be installed and assembled by qualified service personnel.
- Spacings - To ensure safe operation of the equipment installed in the enclosure, per National Electric Code ANSI/NFPA 70, a minimum separation between power cords and signal or communication cables may be required.
- This Cabinet System is for use with Listed wall mounts. Refer to the individual mounts' installation instructions for compatibility.

--SAVE THESE INSTRUCTIONS--


DIMENSIONS



NOTES:


- ELECTRICAL KNOCK OUTS:
 - SINGLE GANG RACO 590.
 - STEEL CITY CY 1/2, OR
 - SIMILAR STYLE ELECTRICAL BOX.
 - 1" AND 2" TRADE PIPE CONDUIT.
- PRODUCT WORKS WITH TS118 AND TS218.

TRIM NOT SHOWN
(USE THESE DIMENSIONS FOR CUTOUT)



SWING ARM SMALL BOX WITH TS118

FULLY RETRACTED MONITOR WILL BE FLUSH WITH WALL
FULLY EXTENDED MONITOR WILL BE 16.55 FROM WALL
MAX TILT IS 12 DEGREES




SWING ARM SMALL BOX WITH TS218

FULLY RETRACTED MONITOR WILL BE FLUSH WITH WALL
FULLY EXTENDED MONITOR WILL BE 16.55 FROM WALL
MAX TILT IS 12 DEGREES

DIMENSIONS: INCHES
[MILLIMETERS]


DIMENSIONS (continued)




LEGEND

	Tighten Fastener Apretar elemento de fijación Befestigungsteil festziehen Apertar fixador Serrare il fissaggio Bevestiging vastdraaien Serrez les fixations		Pencil Mark Marcar con lápiz Stiftmarkierung Marcar com lápis Segno a matita Potloodmerkten Marquage au crayon
	Loosen Fastener Aflojar elemento de fijación Befestigungsteil lösen Desapertar fixador Allentare il fissaggio Bevestiging losdraaien Desserrez les fixations		Drill Hole Perforar Bohrloch Fazer furo Praticare un foro Gat boren Percez un trou
	Phillips Screwdriver Destornillador Phillips Kreuzschlitzschraubendreher Chave de fendas Phillips Cacciavite a stella Kruiskopschroevendraaier Tournevis à pointe cruciforme		Hex-Head Wrench Llave de cabeza hexagonal Sechskantschlüssel Chave de cabeça sextavada Chiave esagonale Zeskantsleutel Clé à tête hexagonale

TOOLS REQUIRED FOR INSTALLATION



PARTS



INSTALLATION



WARNING: IMPROPER INSTALLATION CAN RESULT DEATH OR SERIOUS PERSONAL INJURY! This accessory should be installed by qualified personnel.

Site Preparation

Locate and Prepare Mounting Site

1. Identify a suitable wall location for the in-wall enclosure.

IMPORTANT ! : The TA502 is designed for in-wall installation between two wood studs, 16" on center. Inadequate space will remain on each side between studs for electrical wires/cables, plumbing, ductwork, or insulation. Locate accordingly!



WARNING: ELECTRICAL SHOCK HAZARD! CUTTING OR DRILLING INTO ELECTRICAL WIRES OR CABLES CAN CAUSE DEATH OR SERIOUS PERSONAL INJURY! ALWAYS make certain area behind mounting surfaces is free of electrical wires and cables before cutting, drilling, or installing fasteners.



WARNING: EXPLOSION AND FIRE HAZARD! CUTTING OR DRILLING INTO GAS PLUMBING CAN CAUSE DEATH OR SERIOUS PERSONAL INJURY! ALWAYS make certain area behind mounting surfaces is free of gas, water, waste, or any other plumbing before cutting, drilling, or installing fasteners.

2. Using a stud sensor, locate and mark studs.
3. Center and level housing between marked studs.
4. Using housing as a template, draw pencil line completely around housing.

NOTE: Housing is designed to fit between and directly against two adjacent wall studs. (See Figure 1)

5. Cut drywall on *outside* edge of line and remove.

Frame Housing

IMPORTANT ! : Consult a qualified building contractor to install housing framing and follow all applicable building codes!

1. Cut four 8" long blocks for support framing.
2. Using three #10 x 2-1/2" countersunk wood screws (not provided), attach support framing to the studs (See Figure 2)




Figure 1

NOTE: Ensure screws are far enough from block end to prevent interference with framing screws installed in **In-Wall Enclosure Installation** section.

3. If necessary, cut rectangular hole in horizontal framing to accommodate the PAC-GB1 Listed electrical box accessory (not included).
4. Attach horizontal framing to each support block with two #10 x 2-1/2" countersunk wood screws (not provided). (See Figure 2)




Figure 2

In-Wall Enclosure Installation

1. Install PAC-GB1 Listed electrical box accessory (not included) into the TA502 (A) following instructions included with the PAC-GB1.
2. Connect electrical wiring.
3. Route audio/visual cables into housing.
4. Center TA502 (A) in opening and insert into opening.
5. Align front of box with front face of wall. (See Figure 3)




Figure 3



WARNING: ELECTRICAL SHOCK HAZARD! CUTTING OR DRILLING INTO ELECTRICAL WIRES OR CABLES CAN CAUSE DEATH OR SERIOUS PERSONAL INJURY! ALWAYS make certain area behind mounting surfaces is free of electrical wires and cables before cutting, drilling, or installing fasteners.

6. Drill four 3/16" diameter pilot holes in studs at side mounting holes. (See Figure 3)
7. Attach the TA502 (A) using four M7 x 50mm Allen head connector screws (D) and four spacers (B) into pilot holes using an M4 Allen head drill bit (F). (See Figure 4)

NOTE: The TA502 has 1/2" total clearance between the two studs. The spacers allow side to side adjustment.




Figure 4

8. Drill four 3/16" diameter pilot holes in horizontal framing at mounting holes.
9. Attach the TA502 (A) to horizontal framing using four M7 x 40mm Allen head connector screws (C) using an M4 Allen head drill bit (F). (See Figure 5)




Figure 5



DANGER: IMPROPER WIRING CAN LEAD TO DEATH OR SEVERE PERSONAL INJURY! Grounding must be installed by qualified personnel using a UL Recognized No. 12AWG grounding wire connected to grounding lug on mount.




Figure 6

TS118/218SU Installation

IMPORTANT ! : The TA502 was designed specifically for the TS118SU and TS218SU wall mounts. Do not attempt to install any other wall mounts with the TA502!

1. Use four 5/16-18 x 1/2" button head cap screws (M) to attach bracket (P) to the TA502 (A). (See Figure 7)




Figure 7

2. Partially install 1/4-20 x 1/2" button head cap screw (N) into corresponding hole on attach bracket (P), leaving screw hanging out 1/4" from bracket. (See Figure) or (See Figure 9)
3. Hang TS118/218SU mount onto screw by latching key-shaped hole over screw. (See Figure) or (See Figure 9)




Figure 8




Figure 9

4. Use one (TS118SU) or two (TS218SU) 1/4-20 x 1/2" button head cap screws (N) to attach TS118/218SU to attach bracket (P). (See Figure 10) and (See Figure 11)
5. Tighten all screws to secure TS118/218SU to attach bracket (P). (See Figure 10) and (See Figure 11)




Figure 10




Figure 11

Cable Management

1. Attach all cables to display.
2. If necessary, use cable tie mounts (H) and cable ties (J) to secure cables within TA502.

6. Complete TS118/218SU installation according to corresponding installation instructions.

Trim Kit (Optional)

1. Remove paper covering adhesive and affix three tape squares (K) to inside lower flange of each trim piece (G). (See Figure 12)
2. Orient trim pieces (G). (See Figure 12)
3. Remove paper covering adhesive back from tape squares (K) on trim and press trim (G) against inner wall of box. (See Figure 12)




Figure 12



Our Mounts. **Your Vision.**

Chief, a products division of
Milestone AV Technologies

8800-002233 Rev01
©2015 Milestone AV Technologies
www.chiefmfg.com
10/15

USA/International	A 6436 City West Parkway, Eden Prairie, MN 55344 P 800.582.6480 / 952.225.6000 F 877.894.6918 / 952.894.6918
Europe	A Franklinstraat 14, 6003 DK Weert, Netherlands P +31 (0) 495 580 852 F +31 (0) 495 580 845
Asia Pacific	A Office No. 918 on 9/F, Shatin Galleria 18-24 Shan Mei Street Fotan, Shatin, Hong Kong P 852 2145 4099 F 852 2145 4477

