

The AS-1100 is easy to use. The Any Spot® WPM replaces floor wedges and the amplifiers that power them. Simply plug the ANY SPOT® into a 'monitor out' jack on the mixing console, create the desired mix, and it's ready to deliver quality sound. The AS-1100 has 120 selectable UHF frequencies to help locate the best and clearest signal to transmit. The transmitter (AS-1100T) is selectable to either mono or stereo.

The AS-1100R (receiver) features a 100mw headphone amplifier with a standard 3.5mm (1/8") headphone output. The AS-1100R is sure to be plenty loud for any environment. The receiver has a built in limiter & LCD display.

The AS-1100T (transmitter) has two XLR/1/4" combo jacks for its inputs,

stereo/mono switch, headphone output, volume control, & LCD display. The transmitter includes a single/dual rack mount kit, for mounting one unit in one rack space or mounting two transmitters side by side in one rack space.

The AS-1100 can be purchased with either of our Ear bud upgrades the EB6 (AS-1106) or the EB10 (AS-1110).

The Any Spot® Series of Wireless Personal Monitors is a great alternative for performers who are tired of lugging around heavy and bulky floor monitors and tired of leaving a gig with ringing ears. The AS-1100 allows the user to move freely around the stage and continue to hear the monitor mix.

## A5-1100T

- 120 Selectable UHF Frequencies
- Send a Stereo or Mono Mix to Any Number of Receivers Rubberized Cover for Slip Resistant Use on Belt on Stage
- Trouble Free Wireless Connectivity
- XLR to 1/4" Connection From Any Source Device
- Easy to Read LCD Screen with metering
- Input Level Control
- 1/4" Headphone Output with Volume Control for Easy Monitoring

# **Band Pack System**

The AS-1100-4 Band Pack Systems makes it easy for any band to\_ Get Personal. The system includes four receivers and one transmitter. It is designed to get the whole band wireless in one package. The AS-1100-4 will allow a band to send one stereo mix to 4 individuals. Add as many additional receivers as needed.

## A5-1100R

- High Contrast LCD Screen with Four Bar Battery Indicator
- or Guitar Strap
- Easy to Set Group and Channel Selection
- Built-in Limiter
- Operates on 2 AA Batteries (up to 5 hours Alkaline)
- Lightweight titanium driver EB4 Ear buds Included











## **Specifications:**

## AS-1100 System

Band: UHF Frequencies: 120 Transmitter Output Level: 10 mW **Operating Range:** Under Typical Conditions 300' (92m) Note: actual range depends on RF signal absorption. reflection, interference, and battery characteristics Audio Frequency Response: +/-3dB 70Hz~15kHz Total Harmonic Distortion: <1% @ 1kHz Signal to Noise: 85dBA Maximum Deviation Range: +/-40kHz **Dynamic Range:** >90dB A-weighted Operating Temperature Range: 14°F to 122°F (-10° C to +50° C) Note: battery characteristics may limit this range Included Accessories: Power Supply, EB4 Ear Buds, Antenna, Single/Dual Rack Ears, Quick Start Guide

#### AS-1100T Transmitter

Main Frame Size: EIA STANDARD 1/2U Modulation Mode: FM Standard Modulation RF Output: 10 mW Max Audio input level: +6dBV Gain Adjustment Range: 40dB Audio Input: Line Level x 2, XLR/ 1/4" Combo Jack XLR input: Impedance balanced Pin: 1 Ground (cable shield) Pin: 2 Audio + Pin: 3 No Audio -Dimensions: 1.5" x 8.3" x 3.78" (38 x 212 x 96 mm) (HxWxD) Weight: 21 oz. (605 g) Power Supplied By: 12-18 V DC at 300mA supplied by external power supply

## AS-1100R Body Pack Receiver

Audio Output Level: 100mW Sensitivity: -94dBm for 30dB Stereo Separation: 40dB (at 1kHz) Output Connector: 1/8" (3.5mm) Stereo Earphone Connector **Dimensions:** 3.74" x 2.6" x 1" (95 x 65 x 25 mm) (HxWxD) Weight: 3.5 oz (100 g) without batteries Power Supplied By: 2 (AA) size alkaline or rechargeable batteries Battery Life: About 5 hours (alkaline)

FREQUENCY CODES

**CODE D** 584-607 MHz **CODE L** 655-679 MHz **CODE N** 518-542 MHz



601 E. Pawnee Wichita, KS 67211 316. 263.2852 FAX 316.263.0642 www.galaxyaudio.com Distributed in Canada by Audio Distributors International (ADI) 1275 Newton, unit 6 Boucherville, QC J4B 5H2 Canada 450 449 8177 FAX 450 449 8180





O



AS-1100

AS-1100T Transmitter

EB4 Standard Ear Buds

Specifications subject to change without notice.

MAKERS OF THE ORIGINAL HOT SPOT PERSONAL MONITOR

GALAX