

The EDX Series is a dual channel wireless microphone system. The EDX features 2 internal antennas (1 for each receiver), 16 selectable UHF frequencies on each receiver, and IR Sync transmitters to receiver. The EDX has 2 discreet male XLR outputs and 1 combined 1/4" output on the back of the unit. The output is controlled by a volume control for each receiver, located on the front of the unit.

The EDXR can be used and will sync with either the HH38 handheld or the MBP38 body pack transmitters. Systems with the MBP38 body pack are available with either a lavalier, or headset. Both transmitters feature an on/off switch and are powered by two "AA" batteries. The MBP38 body pack transmitter also features a Mic/0/-10 selector switch for various input level sources.

EDX System

- 200' Range
- Internal Antennas



EDXR Receiver

- Dual Channel Receiver
- 16 Selectable Frequencies AF & RF Level Indicators
 - IR Sync Transmitter to Receiver
 - 1 Mixed 1/4" Output, Two Balanced Male XLR Outputs
 - 2 Internal Antennas (Non-Diversity)
 - Rugged Plastic Casing



EDX OPTIONS -OTHER OPTIONS INCLUDE THE HH38 HANDHELD OR MBP38 BODY PACK







ED)



Specifications:

EDX System

Available Channels: 16 Transmitter Output Level: 10 mW Band: UHF Operating Range: Under Typical Conditions 200' (61 m), actual range depends on RF signal absorption, reflection, and interference. Audio Frequency Response: (+/-3 dB) 60 Hz - 16 kHz Total Harmonic Distortion: (+/-30 kHz deviation 1 kHz tone): <1% Dynamic Range: >90 dB A-weighted Operating Temperature Range: 14°F to 122°F (-10°C to 50°C), battery characteristics may limit this range. Included Accessories: Power Supply, 1/4" to 1/4" Audio Cable x1, Quick Start Guide



Audio Output Level: XLR Connector (into 600 Ohms load) -12dBV 1/4" Connector (into 3k Ohms load) -18dBV Output Impedance: XLR Connector 200 Ohms 1/4" Connector 1k Ohms XLR Output: Impedance balanced Pin 1: Ground (cable shield) Pin 2: Audio + Pin 3: No Audio -Sensitivity: -92dBm Image Rejection: >92dB Dimensions: 1.7" x 8.3" x 5" (42 x 210 x 127 mm)(HxWxD) Weight: 13.6 oz (390 g) Power Requirements: 12-18 V dc at 300mA, supplied by external power supply

Dynamic Cardioid Handheld Transmitter (HH38)

Max Audio Input Level: 0dBV Gain Adjust: Trim pot RF Output: 10 mW Frequency Response: 70Hz - 10kHz Dimensions: 10.8" x 1.9" (275 x 47 mm) (LxDia.) Weight: 6.9 oz (195 g) (without batteries) Power Requirements: 2 "AA" Batteries, alkaline or rechargeable Battery Life: About 8 hours (alkaline)

Body Pack Transmitter (MBP38)

Max Audio Input Level: 0dBV to +20dBV Gain Adjust: Mic / 0dB / -10dB RF Output: 10 mW Input Impedance: 5k Ohms Dimensions: 3.3" x 2.6" x 1" (85 x 65 x 23 mm) (HxWxD) Weight: 2.8 oz (80 g) (without batteries) Power Requirements: 2 "AA" Batteries, alkaline or rechargeable Battery Life: About 8 hours (alkaline)









CODE D 584-607 MHz CODE L 655-679 MHz CODE N 518-535 MHz



Specifications subject to change without notice.



601 E. Pawnee Wichita, KS 67211 316. 263.2852 FAX 316.263.0642 www.galaxyaudio.com Distributed in Canada by Audio Distributors International (ADI) 1275 Newton, unit 6 Boucherville, QC J4B 5H2 Canada 450.449.8177 FAX 450.449.8180

450.449.8177 FAX 450.449.8180 Distributed outside the United States by **TradeLink America, LLC.** 230 Kings Mall Ct., Suite 182 Kingston, NY 12401 MikeH@TradeLinkAmerica.com TEL 1.845.246.6200 FAX 1.845.746.9070

MAKERS OF THE ORIGINAL HOT SPOT PERSONAL MONITOR

