Outerloop 3.5™

Universal Intercom Belt Pack



FEATURES	IL	OL	3.5
» HD Voice (Wide-Band Speech)	•	٠	•
» Connects to Headsets, Phones, ອ Notebooks with Bluetooth Wireless Technology	•	٠	
 » Connects to Phones and Notebooks with 4-conductor 3.5mm Headset Interface 			•
» 2.4 GHz Encrypted Digital Wireless	•		
» 3-pin XLR Male and Female Intercom Jacks	•		
 » Uses Standard 4-Pin and 5-Pin Male or Female Intercom Headset Jacks 		•	•
» Send and Receive Volume Controls	•	•	•
» Push-On, Push-Off Talk Button	•	•	•
» Recessed Sidetone Level control	•	٠	•
» Intercom Powered with 9 Volt Battery Backup	•		
» Number of Hours on one 9 Volt Battery	N/A	10 Hrs	>20 Hrs

A Universal Intercom Belt Pack for your Wireless Device.

Outerloop 3.5[™] provides a wireless link to your intercom system. This universal belt pack provides XLR connections for your existing 4-pin or 5-pin intercom headset, routing audio through a wired connection to your mobile device. Use your mobile device to call into your intercom phone bridge, station phone coupler, or any phone-based intercom app such as Unity Intercom or Clear-Com[®] Agent-IC.

Wired to a Wireless Network. Outerloop 3.5 includes a cable that plugs into the 3.5 mm TRRS headset/earbud jack of your mobile device, providing two-way communications. Separate Send and Receive level controls, a push-on, push-off Talk button, as well as a recessed sidetone level control let you adapt to any situation whether you are around the corner or around the world.

Universality. Adapting to the mixed-up intercom world, model OTL3.5-F features both 4-pin and 5-pin Female XLR headset jacks, while model OTL3.5-M features both 4-pin and 5-pin Male XLR headset jacks.

Interloop and Outerloop shown for comparison



OL = Outerloop 3.5 = Outerloop 3.5


© 2018, **JK Audio, Inc.** 1311 E. 6th St. Sandwich, IL. 60548 800.552.8346 • 815.786.2929 Se Habla Español **jkaudio.com** info@jkaudio.com



Outerloop 3.5™

Universal Intercom Belt Pack

REAR VIEW OUTERLOOP 3.5-F



OUTERLOOP 3.5-M



SPECIFICATIONS

Model Outerloop 3.5-F		
Headset:	4-pin Female XLR, 5-pin Female XLR	
Model Outerloop 3.5-M		
Headset:	4-pin Male XLR, 5-pin Male XLR	
Headset Microphone		
Impedance:	50-2000 ohms	
Headset Earpiece		
Load Impedance:	50-600 ohms	
Power:	>50 mW into 150 ohms	

м	וכר
	1361

Frequency Response:	50Hz - 15 kHz
Power:	9 VDC Battery
Size:	4.7" x 3.75" x 1.65" (12 x 9.5 x 4.2 cm)
Weight:	10 ounces (275 grams)

© 2018, **JK Audio**, **Inc.** 1311 E. 6th St. Sandwich, IL. 60548 800.552.8346 • 815.786.2929 Se Habla Español **jkaudio.com** info@jkaudio.com



CE