

# Digitool® LIVE



## OVERVIEW

The Digitool LIVE is an 8 input, 8 output configuration designed primarily for live audio applications, multi-way house systems and also multiple monitor mix situations. The Digitool LIVE features balanced XLR input and output connections, but does not have the control voltage ports available on the MX models.

## FEATURES

- 8 input, 8 output Live Audio DSP Processor
- Enhanced navigation
- XLR Inputs and XLR Outputs
- Front panel mute switches for all inputs and outputs
- Front panel "edit" button enables access to the encoders for programming.
- 5 segment LED meters for input and output level visualization
- Rear panel Ethernet port for network connectivity, allowing discovery of the Digitool on a network or external
- Front panel USB port provides easy access to connect a laptop for programming purposes.
- NWare based Graphical User Interface
- AES Input that can be assigned to any of the outputs.
- Full color LED display.
- Weight Unpacked: 10.69 lb(4.85 kg)
- Weight Packed: 14.66 lb(6.65 kg)
- Width Packed: 21"(53.34 cm)
- Height Packed: 22.5"(57.15 cm)
- Depth Packed: 6.5"(16.51 cm)