

Saffire PRO 14

8 IN / 6 OUT FIREWIRE AUDIO INTERFACE FEATURING TWO FOCUSRITE PREAMPS



The Focusrite Saffire PRO 14 is a 8 in / 6 out FireWire audio interface designed for the modern home studio environment. An unparalleled preamp legacy forms the foundation, with two award-winning Focusrite preamps. Legendary sonic performance and both digital and analogue I/O combine with Focusrite's established MixControl software to deliver seamless integration, excellent routing flexibility and rock-solid driver stability.

THE SOFTWARE



SAFFIRE MIXCONTROL 18 x 6 ZERO-LATENCY DSP MIXER / ROUTER



FOCUSRITE COMPRESSION, REVERB, GATING AND EQ VST/AU PLUG-INS



ADDITIONAL FEATURES:

- Front-panel headphone output with level dial
- Bus-powering
- Two Hi-Z instrument inputs
- Tactile main monitor dial
- Switchable phantom power
- Software PFL

KEY PERFORMANCE DATA:

A-D Digital Conversion Dynamic Range: 109dB
Noise [mic input]: THD+N = 0.0025%

- **Two high-quality award-winning Focusrite mic pres**
Focusrite interfaces are always the best sounding interfaces in their class.
- **High-quality 24-bit/96kHz FireWire interface**
Features professional conversion and JetPLL™ jitter elimination technology, that provide pristine audio quality and reliable synchronization.
- **Total I/O count of 8 inputs and 6 outputs**
Both digital and analogue I/O are provided, as well as a unique Loopback facility for routing audio between software applications via Saffire MixControl.
- **Saffire MixControl ultra-low-latency DSP Mixer/Router**
This 18 x 6 DSP mixer provides truly-flexible routing and monitoring capabilities alongside intuitive one-click set-up solutions
- **Unmatched routing flexibility**
Set-up for any recording session quickly and intuitively. Route any input signal or sequencer output, or a mix of both, to any of Saffire PRO 14's outputs.
- **Focusrite VST/AU Plug-in Suite, for use in the mix**
Upgrade your standard sequencer effects with Focusrite Compression, Reverb, Gating and EQ VST/AU plug-ins.

CHANNEL COUNT AT A GLANCE

IN	COUNT	FORMAT	CONNECTOR	DETAILS
	2	Mic/line/inst	Combo XLR	Including 2 instrument inputs
	2	Line analogue	1/4" TRS jack	On rear panel
	2	S/PDIF	RCA phono	n/a
	2	Loopback	Virtual	Internally routed software inputs
	16	MIDI	5 pin DIN connector	Provides 16 channels of MIDI
OUT				
	4	Line analogue	1/4" TRS jack	n/a
	2	S/PDIF	RCA phono	n/a
	16	MIDI	5 pin DIN connector	Provides 16 channels of MIDI

Focusrite[®]
THE INTERFACE COMPANY