



Designed to enhance the video you capture with your iPhone 4.











AR-4i Audio Interface for iPhone 4

The iPhone 4 is fabulous and takes great HD quality video. However if there's one area that lets it down, it's the sound. The small internal microphone only records in mono with no control and as for the quality.... Well let's just say it not exactly high-fidelity.

Enter the new Fostex AR-4i. Offering excellent quality stereo audio recording with LED input level metering, gain control and headphone monitoring, the AR-4i has been designed to dramatically increase the quality of the sound of the videos you take with your iPhone 4.

Perfect for TV & Radio reporting, live video streaming to the web, video blogs / YouTube uploads plus ideal for family and domestic use.







Designed to enhance the video you capture with your iPhone 4.

 \Box

The audio quality and versatile operation of the AR-4i make it ideal for both professional applications and domestic / consumer use. For example, in ENG applications where budgets are tight, the AR-4i turns the iPhone 4 into a high quality, hard working audio / video capture device while everyone who shoots video will appreciate the improved sonic quality and audio control the AR-4i brings to the party. Whether you're a reporter, stream video to web services such as Twitter, U-Stream etc., use video upload sites such as YouTube and Vimeo, or simply want to dramatically improve the sound of your videos, the Fostex AR-4i is for you.



Main Features

- Equipped with 3 x stereo inputs (Line/Mic) for using 2 of the 3 simultaneously for vertical or horizontal use
- 2 x plug-in powered condenser cardioid type microphones with pop-shields supplied. Third-party microphones can also be used.
- 4-dot LED level meter for input monitoring
- Thumb wheel input gain control
- Setup App supplied free from App Store for setting Pan (L/C/R), Low Cut Filter, Limiter, etc.
- Headphone output for recording
 & playback monitoring
- Long operation time with 2 x AAA alkaline batteries for 8 to 10 hours
- Supplied with a sturdy hand grip
- 2 x threaded tripod mounts on the bottom and side for use with tripod, camera rigs, etc.
- Cold shoe for use of third-party camera options

AR-4i Audio Interface for iPhone 4

Specifications

Input	
Connector:	3.5mm dia stereo mini
Input impedance:	more than 2k ohm
Gain:	-12 / -59.5dB (variable)
Plug-in power:	2.5V (continuous)
Level Meter LED:	4-dot (doubles as system status indicator)
Phones	
Connector:	3.5mm dia stereo mini
Loaded impedance:	more than 16k ohm
Maximum output:	15mW (32 ohm loaded, THD less than 0.1%)
Audio	
Frequency Response:	20Hz / 20kHz +-4dB (Mic-Phones / 15mW /
	32ohm loaded)
Signal to Noise Ratio:	more than 73dB (Mic-Phones / Input gain
	maximum)
General	
Physical dimensions:	735 (W) x 106(H) x 50(D)mm incl. protrusion
	Hand Grip. 235mm dia x 101mm excl. screw
Weight (approx):	200g (main) / 102g (hand grip)
Power:	2 x AAA batteries (alkaline 3V / Nih 2.4V)
External Power:	USB mini B type (5V)
Power Consumption:	0.3W
Accessories:	2 x cardioid plug in mics, Hand grip,
	Carrying bag, 2 x AAA batteries (manganese)





iPhone App

The dedicated, easy to use iPhone App (available at the App Store) allows for easy control of input level, microphone setting, Equalisation, Filters etc.



Fostex Company, 3-2-35 Musashino, Akishima, Tokyo, Japan 196-0021 Tel: +81 (0)42-546-4974 Fax: +81 (0)42-546-9222

www.fostex.com

In accordance with our policy of continuous development, we reserve the right to change specifications without notice. E&OE.

"Made for iPhone" means that an electronic accessory has been designed to connect specifically to iPhone and has been certified by the developer to meet Apple performance standards. Apple is not responsible for the operation of this device or its compliance with safety and regulatory standards. Please note that the use of this accessory with iPhone may affect wireless performance. iPhone is a trademark of Apple Inc., registered in the U.S. and other countries.