



## ET-PV2UR

V-Mount Adaptor for Blackmagic URSA Camera

IDX continues to expand its V-Mount power solutions by developing a battery plate for the Blackmagic URSA camera, the [ET-PV2UR](#). Tested and approved by Blackmagic Design, the ET-PV2UR mounts directly to the URSA, providing a seamless look and proper power connectivity. In addition, ET-PV2UR's built-in D-Tap (unregulated) allows ancillary accessories to be powered directly off the plate.

In consideration of URSA's high power draw, IDX recommends the following IDX ENDURA batteries: ELITE, E-HL9, E-HL9S, DUO-150, CUE-D150, and E-HL10DS.

*Endura*  
SYSTEM



### ET-PV2UR Features:

- **Direct mount** to Blackmagic URSA
- **Seamless look** and proper power connectivity
- **D-Tap (unregulated)** provides power to ancillary accessories (50W max)
- **Compatible** with all IDX ENDURA High-load capable batteries

### Technical Specification

**D-Tap Output Voltage:**

12~17V DC

**Max. D-Tap Output:**

50W

**Dimensions:**

3.25(W) x 5.59(H) x 0.47(D) inches  
82.5(W) x 142(H) x 12(D) mm

**Weight:**

0.37 lbs. approx.  
170g approx.

**Included Accessories:**

M3 (8mm) screw x 4

