



104R

1:4 RF Distribution Amplifier



The **104R** is a high-performance distribution amplifier for analog RF signals. It takes one RF (CATV/MATV) signal and distributes it to four identical outputs.

FEATURES

- High Bandwidth - 3GHz.
- RF Gain - +6dB across band.
- Compact Kramer **TOOLS™** - 3 units can be rack mounted side-by-side in a 1U rack space with the optional RK-3T rack adapter.



104R

TECHNICAL SPECIFICATIONS

INPUT: 1 RF, 0.5Vpp/75Ω (max.) on an "F" type connector.
OUTPUTS: 4 RF, 0.5Vpp/75Ω (max.) on "F" type connectors.
BANDWIDTH: 40MHz to 3000MHz (+/-3dB).
COUPLING: AC.
RF GAIN: +6dB typical across band.
NOISE FIGURE: 3.5dB.
POWER CONSUMPTION: 12V DC, 80mA.
DIMENSIONS: 12cm x 7.5cm x 2.5cm (4.7" x 2.95" x 0.98") W, D, H.
WEIGHT: 0.32kg (0.71lbs) approx.
INCLUDED ACCESSORIES: Power supply, mounting bracket.
OPTIONS: RK-3T 19" rack adapter.

