



## VA-1VGAN

Computer Graphics Video EDID Emulator

---



The **VA-1VGAN** is an EDID emulator for computer graphics video signals. The unit can capture an EDID setting in non-volatile memory from the output allowing convenient and reliable connection to the source.

### FEATURES

---

- Bandwidth - 1.8GHz.
- Control - Capture button.



## VA-1VGAN

---

### TECHNICAL SPECIFICATIONS

---

INPUT:	1 XGA input on a 15-pin HD (F) connector.
OUTPUT:	1 XGA output on a 15-pin HD (F) connector.
MAX. OUTPUT LEVEL:	>2Vpp.
BANDWIDTH (-3dB):	1.8GHz.
DIFF. GAIN:	0.02%.
DIFF. PHASE:	0.02Deg.
K-FACTOR:	<0.05%.
S/N RATIO:	74dB @5MHz (unweighted: 66dB).
CONTROLS:	Button for EDID capture.
COUPLING:	DC, direct wiring between input and output.
POWER CONSUMPTION:	5V DC, 20mA.
DIMENSIONS:	6.2cm x 6.2cm x 2.4cm (2.4" x 2.4" x 0.9") W, D, H.
WEIGHT:	0.15kg (0.33lbs) approx.
INCLUDED ACCESSORIES:	Power supply.
OPTIONS:	RK-4PT 19" rack adapter.

