

|                       |                                                                       |                                                             |
|-----------------------|-----------------------------------------------------------------------|-------------------------------------------------------------|
| Available lens        | Canon / Fujinon                                                       |                                                             |
|                       | ※Certain lens or digital lens may not be compatible.                  |                                                             |
| Clamping width        | Φ 10-30 mm ( 0.39 - 1.18 inch )                                       |                                                             |
| Connecting cable      | 8 pin ( 12 pin can also be matched by using an A-12P adaptor )        |                                                             |
|                       | ※A-12P ( Optional ) ... Is an adaptor for 8 pin to 12 pin connection. |                                                             |
| Weight                | 0.17kg ( 0.37 lb )                                                    |                                                             |
| Cable length          | 750 mm ( 29.5 inch )                                                  |                                                             |
| Operating temperature | -10°C ~ 40°C                                                          |                                                             |
| Functions             | Lens exchange switch                                                  | C ( Canon ) or F ( Fujinon )                                |
|                       | REC / RET Exchange switch                                             | REC ( Record ) or RET ( Return )                            |
|                       |                                                                       | ※Select either the REC or RET depending on the application. |
|                       | REC/RET Button                                                        | Start / Stop ( for Record or Return )                       |
|                       | Zooming knob                                                          | Continuous variable zoom control                            |

## Remarks

### ■Exterior Dimensions (mm)

