

Model Name	SE-3200
Product Name	HD 12-Channel Digital Video Switcher
Video Standard	Full HD
Video Format	1080p 50/59.94/60Hz, 1080i 50/59.94/60Hz, 720p 50/59.94/60Hz,
Video Processing	SDI: 4:2:2 HDMI: YUV 4:2:2, RGB: 4:4:4
Input Routable / Crosspoint	All 12, repeatable
Video Input	8x SDI, 4x HDMI
Mix HD & SD Source	N/A
Computer Graphic Interface	4 via HDMI
Video Output	6x SDI Outputs Assignable: PGM, PVW, PGM Clean & Multi-View, Input 1-12 3x HDMI Assignable: PGM & Multi-View
Down-converted output	N/A
Built-In Multi-View Monitoring Out	HDMI
Audio Input	4x Balanced XLR
Audio Output	2x Balanced XLR
Embedded Audio Support	Embedded 4-CH Audio Output
Audio Delay Calibration	up to 16 Fields or 8 Frames per Channel
A+V Switching	Yes
Chromakey	4
USK	4x USK support Chromakey & Linear/ Luma Key
DSK	2x DSK support Lumakey & Linear key (Key / Fill)
Picture in Picture	8 (4x PIP, 4x Flex Source)
Logo Insertion	2
Still Store	500
Effects	DVE, FTB, Cut, 32 Wipe with border

Transition Preview	Full Transitions Preview
Sync / Reference In/Out	Built-in Genlock Support external sync with loop thru
Tally Output	1x D-sub 25pin, Dual Color
PC Remote Control	Via Ethernet (free Window software) or RS-422 / RS-232
Built-in Audio Mixer	N/A
Special Features	4 User Memory Preset Free Virtual Set and Stinger Transition included
Chassis	2 units, 2RU Rack-Mount Mainframe
Power	DC 12V 69W
Accessory	CB-60/61/62 (30/50/100m)