

ANY SPOT[®] TRAVELER

TV5X

ALL INCLUSIVE PORTABLE PA SYSTEM

The new TV5X is one of the latest models in the Traveler Series by Galaxy Audio. The Traveler Series is a line of powered speakers with built in batteries. All models in the Traveler Series can be run from either AC or the built in battery.

Most Traveler Series products are configurable to include built in CD/media players, UHF wireless microphones, Bluetooth[®] receiver, or Audio Link Transmitter. Each item is built to order. Travelers are designed to be portable and used in a wide array of applications, like classrooms, churches, meeting rooms, graveside, auctions, among many others.

The TV5X has a built in 40 watt power amplifier with a 5" full range woofer and tone control. The TV5X, like other models in the Traveler Series, can be configured with up to two UHF wireless receivers or a Bluetooth[®] receiver. Each UHF receiver has two different handheld mics and two body pack transmitters to choose from. There is also an optional MP3 player available which can play MP3s from USB or SD card.

The TV5X has a 1/4" mic input with volume control, 1/8" input and output, and 4 bar battery level indicator. The built in Voice Priority, when activated, will lower the volume of the music when it receives a signal from a wireless or handheld microphone. This is convenient as you will not need to adjustment the volume of your music when needing to make announcements.

The TV5X is constructed from durable plastic and can be set on a table top, or on an optional tripod stand. The TV5i has a built in handle and shoulder strap for easy transport. The TV5X weighs 7lbs. An optional carrying bag is available.

- Built in Shoulder Strap
- 4 Wireless Microphones Optional
- One Wired Microphone Input
- Optional Bluetooth[®] Receiver
- Optional Media Player
- Four-bar battery Indicator



Available with TRAVELER BAG



* A Limited 90 Day Warranty Applies to Rechargeable Batteries

MAKERS OF THE ORIGINAL
HOT SPOT[®] PERSONAL MONITOR

ANY SPOT[®] TRAVELER

TV5X

Specifications

- Sensitivity:** 88 dB, 1 Watt @ 1 M
- Maximum SPL:** 104 dB
- Frequency Response:** 70 Hz ~ 16 kHz (audio)
- Speakers:** 5" Neolite Speaker
- Receiver Module:** AS-TVREC x 2 Diversity (optional)
- Output Power:** 40 W (RMS) @ 4ohm
- Signal to Noise Ratio:** Up 70 dB
- Optional Media Player:** AS-DIGIMP5 (optional)
- Audio Input:** 1/4"-Mic. In, 1/8"-Aux In
- Audio Output:** 1/8"-Aux Out
- Controls:** Master, Tone, Aux In, Mic
- Wireless Range:** 150' (50 meters) to 220' (70 meters)
- Power Supply:** 20VDC 3.25A
- Battery:** 12V, 2.9Ah (Lead-Acid) Rechargeable Battery
- Running Time:** 4 ~ 5 Hours
- Charging Time:** 3 ~ 4 Hours
- Dimensions:** 13.11" x 6" x 9.7" (333 x 153 x 246 mm)
- Weight:** 7 lbs (3.1 kg)

OPTIONS/SPECIFICATIONS



Available with
Bluetooth[®]
TV5-RECBT, TV5-DREC,
TV5-REC, &/or TV5MP3
Wireless Mic Receiver up to 4

Master Control Panel
with Battery Level, Mic in

Rechargeable Battery & Charger



TVBPT

- Pendant Transmitter
- 96 Channels
- Lightweight Compact Size
- Soft Touch Buttons
- LCD Display
- Built in Microphone
- External Mic input
- Auxillary Line Input
- Two power settings 10 mW and 1mW
- Rechargeable Lithium Battery
- Single Charger Included
- Contacts for Optional Cradle Charger
- Removable Belt Clip



TVH2

- Condenser Handheld
- 96 Channels
- Lightweight Compact Size
- Channel Up, Set & Down Selector
- Back Lit LCD Display
- Talk/Mute Soft Touch Button
- Two Power Settings 10mW, 1mW
- 150' Range
- Runs on 2 AA Batteries (about 12-16 hrs)
- Charging Base Terminals



TVHH

- 96 Selectable Channels
- Channel Selector
- LCD Display
- Dynamic Capsule
- Built-in-Antenna
- 3-Bar Battery Condition Indicator
- Hi/Low Volume + Mute Switch
- Runs on 2 AA Batteries (14 hrs)
- DC Charging Input
- 8.3 oz. (280g)



TVMBP

- 96 Selectable Channels
- Channel Selector
- LCD Display
- Belt Clip
- 3-Bar Battery Condition Indicator
- Mute Switch
- Mic Input
- Aux Input
- Runs on 2 AA Batteries (14 hrs)
- 4.4 oz. (170g)
- Available with the HS-U3BK Headset or the LV-U3BK Lavalier

Optional DC chargers



LV-U3BK

- Uni Directional Element
- Freq. Response 50Hz - 19kHz



AS-DCTVHH
For TVHH



AS-DCTVMBP
For TVMBP

TV5X Bag
Protective Bag With
Control Panel Access



- 96 Selectable Channels
- Channel Selector
- RF and AF indicator
- Volume Control
- LCD Display
- Table Top/Rackmount Transmitter



HS-U3BK

- Uni Directional Element
- Freq. Response 50Hz - 18kHz



AS-DCBPTR
For AS-TVBP,
TVBPT, & TVH2



MAKERS OF THE ORIGINAL
HOT SPOT PERSONAL MONITOR

* A Limited 90 Day Warranty Applies to Rechargeable Batteries Specifications subject to change without notice.

601 E. Pawnee Wichita, KS 67211 316. 263.2852 FAX 316.263.0642 www.galaxyaudio.com

Distributed outside the United States by **E and E Exports, Inc.** 2815 Junipero Ave. Suite 101 Signal Hill, CA 92614
562.988.3447 FAX 562.989.3037

Distributed in Canada by **Audio Distributors International (ADI)** 1275 Newton, unit 6 Boucherville, QC J4B 5H2 Canada
450.449.8177 FAX 450.449.8180

V20150402